

4MP QHD SMART Video Doorbell

Wired

QHD 4 MP

PS-5G 501 Ai **WIFI**



works with
Google Assistant

WORKS WITH
amazon alexa



APP Video Calling

สามารถมองเห็นหน้า และ
คุยโต้ตอบ ผ่าน Doorbell ได้



AI Detection

มีระบบตรวจจับความเคลื่อนไหว
ที่สามารถตรวจสอบใบหน้าได้



Infrared Night Vision

สามารถมองเห็นได้แม้ใน
ที่มืดสนิท



Weather Resistant

กันน้ำได้ระดับ IP65



รับประกัน **2 ปีเต็ม**

ITEMS		Pixels Video Doorbell
Image Sensor	Sensor	High Definition Color CMOS Sensor
	Display Resolution	2688*1520 (4.0M Pixels)
	Min. Illumination	N/A (Without IR Illuminator)
Lens	Lens Type	Glass Lens
	focal length	19mm
	Aperture	F 2.0
	Angle of view	Diagonal:170°,Horizontal:152°,Vertical:91°
Video	Image Compression	H.265/H.264
	Image Frame Rate	Max 25fps (2K)
	Resolution	2K(2560x1440),1080P(1920x1080),720P(1280 x 720)
	Stream	Dual stream
	HDR	Support HDR
	Flip image	Flip and mirror
	Infrared mode	1pcs 850nm SMD IR-LEDs
	Night mode	Manual and automatic modes
Audio	Night visibility	5 m
	Input/Output	Build-in mic and speaker,support full duplex real-time 2-way Audio
	Audio Compression	AAC
Network	Ethernet	Transfer via Type C to RJ45
	Wireless Standard	2.4GHz&5GHz,IEEE802.11b/g/n/ac
	Wireless Security	WPA, WPA2
	Remote Access	P2P
	Wifi configuration mode	Support scan QR code , sound wave to add camera
	Network Protocol	IP, TCP, UDP, SMTP, FTP, RTSP
Software Features	Motion Detection	Alarm via E-Mail, upload alarm snapshot to FTP , push message to mobile phone and push stream to Cloud
	Sound Detection	Alarm via E-Mail, upload alarm snapshot to FTP , push message to mobile phone and push stream to Cloud
	Face Detection	Alarm via E-Mail, upload alarm snapshot to FTP , push message to mobile phone and push stream to Cloud
	Face Recognition	Support up to 20 family members
	Privacy Block	Yes
	User Accounts	Three levels user role
	Firewall	Supports IP Filtering
	Custom ringtones	Support to customize exclusive ringtones through mobile APP
	Micro SD card	Support maximum 128GB Micro SD card storage
	Foscam NVR	Compatible with Foscam NVR
	Foscam VMS	Compatible with Foscam VMS
	Visitors leave a message	Support the push of guest messages to the APP
Power	Reset	Reset button is available
	Power Supply	AC8-24V or DC5-30V
	Power Consumption	5 Watts (Max.)
Physical	Dimension(LxWxH)	115(L)x45 (W)x25 (H) mm
	Net Weight	125g
Accessories	Power Kit	1pcs(work with existing electronic chime)
	Leveler	1pcs(Pre-install the Leveler on the mounting plate)
	Mounting bracket	Flat Mounting Plate*2pcs,Horizontal Wedge*1pcs,Vertical Wedge*1pcs
	Connector	U-type Connector*1pcs,Fork Connector*1pcs
	Doorbell Wire Extenders and Nuts	With 1pcs extra screw for backup (for AC power of Doorbell), pre-install 2 Wire Extenders on the Doorbell bod
	L-shape Screwdriver	1pcs
	Screws	Wall Mount Screws*1sets,Anti-theft Screws*2pcs
Environment	Waterproof	IP65
	Operating Temperature	-20°C~ 50°C (-4°F ~ 122°F)
	Operating Humidity	20% ~ 85% non-condensing
	Storage Temperature	-20°C ~ 60°C (-4°F ~ 140°F)
	Storage Humidity	0% ~ 90% non-condensing
Certification	CE, FCC, RoHS,WEEE	

ดาวน์โหลด Application
PIXELS HOME



Pixels Cloud



Cloud Management
Access, manage and control
your cameras



Cloud Push
Get real-time text or image alert
notifications on your phone



Cloud Recording
Store alarm or continuous video
recordings in the cloud



Cloud Playback
See the whole event in your
video history